

# KPS-MT70

Pocket size Digital Multimeter

SKU: KPSMT70CBINT



## Main Features:

- Pocket size digital multimeter
- 6000 counts
- DC/AC voltage, DC/AC current, resistance, capacitance and frequency measurements.
- Diode check and continuity buzzer.
- TRMS measurements.
- Non-contact voltage detection (NCV)
- Battery tester (1.5V)
- Data hold.
- Auto range, auto-off, display backlight and low battery display.
- Built-in test leads.
- CAT. III 600V according to EN61010.



Parameter	Ranges	Resolution	Accuracy
DC Voltage	600mV/6V/60V/600V	0,1mV/1mV/10mV/100mV	± (0,5%+3 digits)
AC Voltage	6V/60V/600V	1mV/10mV/100mV	± (1,0%+3 digits)
DC Current	600µA/6000µA/60mA/600mA	0,1µA/1µA/0,01mA/0,1mA	± (1,0%+5 digits)
AC Current	600µA/6000µA/60mA/600mA	0,1µA/1µA/0,01mA/0,1mA	± (1,8%+3 digits)
Resistance	600Ω/6KΩ/60KΩ/600KΩ/6MΩ	0,1Ω/1Ω/10Ω/0,1KΩ/1KΩ	± (0,7%+3 digits)
	60MΩ	0,01MΩ	± (2,0%+3 digits)
Capacitance	6nF	0,001nF	± (3,0%+8 digits)
	60nF/600nF	0,01nF/0,1nF	± (3,0%+8 digits)
	6µF/60µF/600µF	1nF/10nF/100nF	± (3,0%+8 digits)
Frequency	10Hz – 10kHz	-	± (1,5%+15 digits)
Duty cycle	0,5% - 99,9%	0,1%	± (2,0%+5 digits)



info.emea@mgl-intl.com

+34 985 08 18 70

Parque Empresarial de Argame  
C/Picu Castiellu, parcela i-4, 33163  
Morcín-Asturias (Spain)

AN MGL BRAND